

### L1/L2/L5 GNSS ITS Kit Technical Product Data

#### **Features**

- High Gain Amplified Roof Antenna
  - o Provides 35 dB gain via internal LNA.
- Kit Mounting Hardware
  - Roof Antenna Mounts & Re-Radiating Amplifier Mount included.
- Re-Radiating Variable Gain Amplifier with LCD Screen & Push Button Adjustments
  - Adjustable gain from 0 dB to 30 dB in 1dB increments.



### **Description**

The L1/L2/L5 GNSS Indoor Testing Solution (L125G-ITS) comes with everything required to build a re-radiating system that can broadcast all major GNSS frequencies indoors. GNSS signals received by the roof antenna are amplified and re-radiated to indoor GNSS receivers, eliminating the need to attach receivers directly to the roof antenna. The L125G-ITS consists of an active roof antenna, a passive re-radiating antenna, and a re-radiating amplifier (L125GVGLCDITSAMP) with an external power supply that powers the entire system. 50 ft of LMR400-UF coaxial cable is provided to connect the roof antenna to the re-radiating kit. The L125G-ITS will transmit GNSS signals indoors to receivers over 100 feet away, with all necessary mounts and adapters included in the kit.

In the standard Networked (Externally Powered) configuration, the re-radiating amplifier output (**J1**) is DC Blocked.

#### **Use Cases**

- To re-radiate signal indoors for GNSS product testing.
- To maintain GNSS signal lock for military vehicles parked indoors.
- To facilitate faster GNSS signal acquisition for military aircraft inside a hardened hangar.
- In combination with one of our splitter devices to create a GPS distribution network.



## Re-Radiating Amplifier Electrical Specifications, TA=25°C

**General Specification** 

<u>Parameter</u>	<u>Notes</u>	Min	Тур	Max	<u>Unit</u>
Frequency Range	Covers all major GNSS constellations.	1.1		1.7	GHz
Characteristic Impedance	Input and output ports matched to $50\Omega$ .		50		Ω
Req. DC Input V.	Operating Voltage Range.	3.3		15	VDC
Current Draw	Typical current consumption.		36	40	mA

GPS L1 & L2 RF Specification (1)

<u>Parameter</u>	<u>Notes</u>	Min	Тур	<u>Max</u>	<u>Unit</u>
Min Gain	The relative increase in signal power provided by the amplifier when set to minimum gain.	-1	0	1	dB
Max Gain	The relative increase in signal power provided by the amplifier when set to maximum gain.	29	30	31	dB
Input SWR	Input Standing Wave Ratio: S11			2.0:1	-
Output SWR	Output Standing Wave Ratio: S22			2.0:1	-
Noise Figure	The increase in noise power relative to an ideal amplifier.		L1:2.00 L2:4.25		dB
Band Gain Flatness	The difference in loss or gain between the L1 and L2 frequencies.		0.5	1.0	dB
Group Delay	The transmit time for the signal passing through the device.		L1:1.5 L2:2.1		ns
Reverse Isolation	Attenuation applied signals traveling backwards through the amplifier: S12.		L1: -55 L2: -60		dB
Input P1dB	The 1dB compression point.		L1: -21.5 L2: -23.0		dBm
3rd Order Intercept	Third-order intercept point at L1.		-14		dBm

<sup>(1):</sup> Performance is slightly reduced around GPS L5. If working on sensitive L5 applications, please request performance data.

	External Power Options (Networked Option)					
	Voltage Input	Style				
	110VAC	Transformer (ITA Type A Wall Mount)				
Source Voltage Options	220VAC	Transformer (ITA Type C Wall Mount)				
Course Forage options	240VAC (United Kingdom)	Transformer (ITA Type G Wall Mount)				
	Customer Supplied DC 9-32 VDC	MIL-DTL-5015 10SL Two-Pin DC Connector (Includes Mate)				
	DC Voltage Out	Max Current out For Corresponding Vout				
	3.3 V	110mA				
	5V	130mA				
Output Voltage Options <sup>(2)</sup>	9V	140mA				
Output Voltage Options	12V	180mA				
	15V	220mA				
	Custom	Custom				
Standard DC Configuration without External Power Option						
	All Ports Pass DC					
Standard DC C	onfiguration with any External Power Option (AC/D	C or Military DC)				
	J1 Port DC Blocked with 200Ω load standard					
	Antenna Port is DC Pass					
	Connector Style	Charge				
	Type N-female	No Charge				
Connector Ontions	Type SMA-female	No Charge				
Connector Options	Type TNC-female	No Charge (Standard)				
	Type BNC-female	No Charge				
	Other	Contact GPS Networking				
(2): With Network Ont	ion, any RF port (input or output) can be specified t	o Pass DC or Block DC				

(2): With Network Option, any RF port (input or output) can be specified to Pass DC or Block DC



### L125GPSA-T Roof Antenna Electrical Specifications, TA=25°C

<u>Parameter</u>		<u>Notes</u>		Min	Тур	Max	<u>Unit</u>
Frequency	Receiv	relives and amplifies all major GNSS constellations		1539 1164		1610 1300	MHz
Axial Ratio	Ratio betwee	n the major and minor axes of the polarization ellip	se.			0.5	dB
LNA Gain	The relative	ncrease in signal power provided by the internal LI	NA.		35		dB
Antenna Gain	The increase	in signal power relative to an isotropic antenna sou	ırce.		3.4		dBic
GPS L1 Bandwidth		Passband centered at GPS L1 frequency.			71		MHz
GPS L2/L5 Bandwidth	Pas	band covering the GPS L2/L5 frequencies.			136		MHz
Filtering	Out	Out of band rejection +/-50MHz from band-edge		-35	-45	>-80	dB
Noise Figure	The incr	e increase in noise power relative to an ideal amplifier.			3.0		dB
Output SWR	Outpu	t Standing Wave Ratio: S22 over the passband.			1.5:1	2.0:1	-
Characteristic Impedance		Output port matched to $50\Omega$ .			50		Ω
Req. DC Input V.		Operating Voltage Range.		2.3		16	VDC
Current Draw		Typical current consumption.				40	mA
Polarization							
Right Hand Circular Polarization							
Connecto	or Options	Connector Style Type TNC-female	Charge No Charge				

### L125GRRKPA-T Re-Radiating Antenna Electrical Specifications, TA=25°C

<u>Parameter</u>	<u>Notes</u>		<u>Min</u>	Тур	<u>Max</u>	<u>Unit</u>	
Frequency	Receiv	Receives and amplities all major CNSS constellations		1539 1164		1610 1300	MHz
Axial Ratio	Ratio betwee	n the major and minor axes of the polarization ellip	se.			0.5	dB
Antenna Gain	The increase	ncrease in signal power relative to an isotropic antenna source.			3.4		dBic
Output SWR	Outpu	Output Standing Wave Ratio: S22 over the passband.			1.5:1	2.0:1	-
Characteristic Impedance		Output port matched to 50Ω.			50		Ω
Beamwidth	Th	The 3dB angular width of main emission lobe.			120		۰
Polarization							
Right Hand Circular Polarization							
Connecto	Connector Options Connector Style Charge Type TNC-female No Charge						

### **Kit Contents**

- 1 x L125GVGLCDITSAMP
  - Variable gain GNSS reradiating amplifier with LCD screen. Provides 0-30 dB of gain.
- 1 x L125GPSA-T
  - o 35dB active GNSS roof antenna.
- 1 x L125GRRKPA-T
  - Passive GNSS reradiating antenna.
- 1 x Installation Instructions

- 1 x L125GRAMB
  - o L-bracket L125GPSA-T mount.
- 1 x L1RAMB
  - Pipe and flange mounting pole.
- 1 x WRUMT
  - Reradiation amplifier mount.
- 1 x 50' LMR-400-UF CABLE T(m)
- 1 x TNC(m)-TNC(m) RF ADAPTER
  - Mounts the L125GRRKPA-T antenna to the amplifier.





**Part Number Configuration** 

<u>L125G-I15</u> <u>N / 5 / 110</u>
Re-Radiating Kit Type:
L125G-ITS = L1/L2/L5 GNSS Indoor Testing Solution / / /
Connector Options (Type Female Standard):  T= TNC(Standard); N= N-type; S= SMA; B= BNC
OC Output Voltage:
5 = Amplifier Output Voltage (Included antenna requires 2.5 - 15VDC. 5VDC is default voltage)
Source Voltage (Power Supply Options): ————————————————————————————————————
110 = 110VAC, 220 = 220VAC (2 prong Euro), 240 = 240VAC (3 prong UK),
MC = Military DC Connector (User supplies DC voltage range 9-32VDC)

(Military DC Mating Connector is included standard with the MC power option).

When no external power supply option (AC or DC) is selected, Output 1/J1 is Pass DC Standard. When external power supply option is selected, all outputs are DC blocked standard.


Contact GPS Networking Technical Support at 1-800-463-3063 or salestech@gpsnetworking.com for any questions regarding non-standard configurations and corresponding part numbers.





#### **Performance**

L125GVGLCDITSAMP (Standard Gain)


Each L125G-ITS kit ships with a test sheet for the included L125GVGLCDITSAMP that verifies critical performance characteristics, such as gain, input VSWR, and amplitude balance; a typical VNA test sheet is shown below









### GPS Networking PN: L125GRRKPA-T








	DRAWING REVISIO	N HISTORY	
REV	DESCRIPTION	DATE	BY
1	INITIAL RELEASE	2022-09-25	MP














Mechanical Dimensions: Depth: 2.51"
Width: Top Plate: 3.26"
Baseplate: 2.51"
Height: 6.15" Weight: 13.3oz (377g) MAX Operating Temperature Range: -57°C to +87 Materials: Aluminum Zinc Steel

GPS NETWORKING
373 E. Industrial Blvd. Pueblo West, CO 81007

Tolerances: